FTA 6500 PLUS

SD DVB-S MPEG-2 FREE TO AIR

Qty / CT: 24 pcs

SET-TOP BOX

WITH USB PVR AND TIME SHIFT

Main Processor: Ali M3329D
SDRAM size: 16MB
Flash size: 2MB

Digital Satellite receiver compatible with DVB-S standard
Video resolutions: 576p (SD), 576i (SD),
Video recording (with external HDD) with the possibility to record a channel while watching another (MUX).

Playback (from external HDD or Pen drive) of video (MPEG,MPEG4), Photos (JPG, BMP). *OPTIONAL

TImeshift: possibility to pause live programs

VIdeo outputs: SCART x1, rgb/cvbs
Audio out: coaxial
Dolby Digital compatible
Aerial out: Loop - USB 2.0 port

4000 TV & Radio channels / Easy to use
Quick installation and multi-language menus
Various channel functions, Timer function
Auto standby: switches off after 3 hours of inactivity
Formats: 16:9, 4:3 (LB, PS)
NTSC / PAL conversion
Dual audio (if available)
Display type: no

RF input: F-TYPE
RF output: F-TYPE
Receiving channel range: 950 - 2150Mhz
Demodulation: ETS300 421 compliant
LNB controlling: 22Khz - 13/18V

Voltage: 120-220 V
Power consumption: 5W
Accessories: Remote control
SCART: optional / AV cable: no
Dimensions: 138x100x35 mm
Weight: 0.50 Kg

DIGIQuest